

# TR-B200S-LF-WH, TR-B200S-LF-IV

## Low Frequency Intelligent Sounder Base

TRIGA Life Safety Systems, LLC  
7600 Olde Eight Rd.  
Hudson, Ohio 4426-1057

This model is compatible with Models MDL, MDL3R, MDLW, MDL3W and SYNC-1

Tel: +1 330-577-5199. Email: info@trigaglobal.com

**SPECIFICATIONS**

Base Diameter: 6.875" (17.46 cm)  
 Base Height (less sensor): 2.0" (5.08 cm)  
 Weight: 0.6 lb. (272 g)  
 Operating Temperature Range: Refer to the applicable sensor's operating temperature range provided in the sensor's installation manual.  
 Operating Humidity Range: 10% to 93% relative humidity (non-condensing)

**External Supply Electrical Ratings**

External Supply Voltage:	16 to 33 VDC (VFWR)	
Standby Current:	550 µA maximum VDC	
Alarm Current:	High volume setting:	70 mA maximum @ 33.0 VDC
		90 mA maximum @ 24.0 VDC
	Low volume setting:	15 mA maximum @ 33.0 VDC
		20 mA maximum @ 24.0 VDC
		25 mA maximum @ 16.0 VDC

**SLC Electrical Ratings**

SLC Operating Voltage: 15 to 32 VDC  
 SLC Standby Current: 300 µA maximum (base only, refer to applicable sensor specification)

**Sound Output**

High Volume: Greater than 85 dBA minimum measured in a UL reverberant room at 10 feet (3.1m), 24 Volts (in continuous tone)  
 Low Volume: Greater than 75 dBA minimum measured in a UL reverberant room at 10 feet (3.1m), 24 Volts (in continuous tone)

**BEFORE INSTALLING**

Read *Applications Guide for System Smoke Detectors*, which provides detailed information on sensor spacing, placement, zoning, wiring, and special applications. NFPA 72 and NEMA guidelines should be observed. The National Fire Alarm Code, NFPA 72, requires effective January 1, 2014, that audible appliances installed in sleeping areas produce a low frequency alarm signal that shall be a square wave or provide equivalent awakening ability with a fundamental frequency of 520 Hz +/- 10%.

**NOTE:** Triga Series sounder bases are not compatible with remote test capable Triga Series detectors.

**NOTICE:** This manual should be left with the owner/user of this equipment.

**IMPORTANT:** The detector used with this base must be tested and maintained regularly following NFPA 72 requirements. The detector should be cleaned at least once a year.

**GENERAL DESCRIPTION**

The TR-B200S-LF-WH and TR-B200S-LF-IV sounder bases are used with addressable detector heads. Refer to the appropriate manual for more information on sensors.

The TR-B200S-LF-WH/TR-B200S-LF-IV low frequency sounder base generates a low frequency tone around 520 Hz. Studies have shown that low frequency audible devices that operate around 520 Hz are more effective in waking individuals in sleeping areas.

The sounder base is capable of producing a variety of tone patterns, including the distinctive three-pulse temporal pattern (ANSI Temporal 3) fire alarm signal now required by NFPA 72 for commercial and residential applications. The TR-B200S-LF-WH/TR-B200S-LF-IV offers maximum flexibility in configuration and operation to meet or exceed the requirements of UL268 and UL464 for Continuous, Temporal 3 and March time patterns. The temporal 4 pattern meets all requirements of UL268 and UL2075, as well as, private mode setting of UL 464.

The TR-B200S-LF-WH/TR-B200S-LF-IV can be commanded by the Fire Alarm Control Panel (FACP) to adopt the address of the attached sensor head, but as a unique device type on the loop. By using the address, the FACP can command an individual sounder base to activate, or a group of sounders in a suite or other multi-room configuration. The command set from the panel can be tailored to the specific event, allowing selection of volume, tone, and group. The device offers two volume levels: 75 dBA and 85 dBA. The available tones are Continuous, ANSI Temporal 3, ANSI Temporal 4, and March Time. In addition, some panels will offer the ability to command a custom tone pattern. Refer to the appropriate FACP manual for more information.

In addition, the TR-B200S-LF-WH/TR-B200S-LF-IV is equipped with the circuitry to recognize the System Sensor synchronization protocol, enabling the sounder base to be used as a component of the general evacuation signal – producing an NFPA 72 compliant Temporal 3 pattern in synchronization with compatible listed notification devices. This requires connection to a power supply capable of generating the System Sensor synchronization pulses, a FACP NAC output configured to System Sensor synchronization protocol, or a separate synchronization module.

The sounder base is intended for use with intelligent systems. In addition to being connected to the SLC, the sounder base requires a connection to either 24 VDC constant power or a NAC circuit, depending on the FACP and intended use. The connections for 24V constant/NAC power and the communication loop are isolated to prevent electrical interaction between them.

When connected to a NAC, power is supervised via the NAC circuit supervision while in standby mode (EOL resistor required for Class B operation). When activated, the TR-B200S-LF-WH/TR-B200S-LF-IV provides supervision of NAC power. (See Figure 5.)

When using a FACP equipped with a “sounder base standby power monitoring” mode and constant 24 V power, power supervision EOL devices (supervision relays and resistors) should not be used. (See Figure 4.) In this case, the TR-B200S-LF-WH/TR-B200S-LF-IV will provide supervision in both standby and alarm/active mode. Refer to FACP installation documentation to determine if this mode is available. If your FACP does not support this mode or you choose not to use it, power supervision relays and EOL resistors are required to provide supervision in standby mode.

**NOTE:** If the FACP’s “sounder base standby power monitoring” mode is enabled, connecting TR-B200S-LF-WH/TR-B200S-LF-IV low frequency sounder bases to the NAC will result in power supervision failure when in standby. Only connect TR-B200S-LF-WH/TR-B200S-LF-IV low frequency sounder bases to constant 24 V power in this case. Refer to the FACP manual for maximum allowable number of units per loop.

**NOTE:** For NFPA72 Installations, the Temporal 3 tone at high volume should be used for public mode evacuation. The use of other tone styles and low volume level will be at the discretion of the local Authority Having Jurisdiction (AHJ).

**NOTE:** When not used as a supplementary evacuation system, the external 24 VDC supply shall be treated as a component of the main power supply system and shall fall under the requirements of the main power supply system per NFPA 72.

## WIRING GUIDELINES

All wiring must be installed in compliance with the National Electrical Code and the local codes having jurisdiction and must not be of such length or wire size which would cause the base to operate outside of its published specifications. The conductors used to connect smoke sensors to control panels and accessory devices should be color coded to reduce the likelihood of wiring errors. Improper connections can prevent a system from responding properly in the event of a fire.


Wire sizes up to 12 AWG (2.5 mm<sup>2</sup>) may be used with the base. The sounder base will be shipped with the screw terminals set for 14 AWG wiring. If 12 AWG wire is to be used, back out the screws to allow the wire to fit beneath the clamping plates. For best system performance, the power (+ and -) wires and the communication circuit wires should be twisted pair or shielded cable installed in a separate grounded conduit to protect the communication loop from electrical interference.

Make wire connections by stripping about  $\frac{3}{8}$ " (10 mm) of insulation from the end of the wire. Then, slide the bare end of the wire under the appropriate clamping plate (See Figure 1), and tighten the clamping plate screw. Do NOT loop the wire under the clamping plate. (See Figure 2.) The wiring diagram for a typical 2-wire intelligent system is shown in Figure 4.

### CAUTION


For system monitoring - for terminals 2, 3, 4, and 5, do not use looped wire under terminals. Break wire run as shown in Figure 2 to provide monitoring of connections.

FIGURE 1.



C0471-08

FIGURE 2.




C0473-00

## TR-B200S-LF-WH/TR-B200S-LF-IV TERMINALS

No. Function

1. Not Used
2. Positive (+) Comm. Line In and Out
3. Negative (-) Comm. Line In and Out
4. External Supply Positive (+)
5. External Supply Negative (-)
6. Remote Annunciator

## FIGURE 3. MOUNTING



C0891-09

## MOUNTING

Mount the TR-B200S-LF-WH/TR-B200S-LF-IV mounting plate directly to an electrical box. The plate will mount directly to 4" (10.2cm) square (with and without plaster ring), 4" (10.2cm) octagon, 3½" (8.9 cm) octagon, single gang or double gang junction boxes.

1. Connect field wiring to terminals, as shown in Figure 1 and 2.
2. Attach the mounting plate to the junction box as shown in Figure 3.
3. To mount the sounder base, hook the tab on the sounder base to the groove on the mounting plate.
4. Then, swing the sounder base into position to engage the pins on the product with the terminals on the mounting plate.
5. Secure the sounder base by tightening the mounting screws.
6. Install a compatible smoke sensor as described in the installation manual for the sensor.

### CAUTION

Do not over tighten mounting plate screws; this may cause mounting plate to flex.

## TAMPER RESISTANT FEATURE

NOTE: Do not use the tamper-resist feature if the removal tool is to be used. This detector base includes a tamper-resist feature that prevents its removal from the base without the use of a tool. To activate this feature, break the tab from the detector base as shown in Figure 7A. Then, install the detector. To remove the detector from the base once the tamper-resist feature has been activated, insert a small-bladed screwdriver into the slot from the top and press down on the lever. (See Figure 7B). This allows the detector to be rotated counterclockwise for removal. The tamper-resist feature can be defeated by breaking and removing the plastic lever from the base. However, this prevents the feature from being used again.

## TESTING AND MAINTENANCE

Sensors and bases must be tested after installation and as an integral part of a periodic maintenance program. Test the TR-B200S-LF-WH/TR-B200S-LF-IV as follows:

NOTE: Before testing, notify the proper authorities that the smoke sensor system is undergoing maintenance and, therefore, will be temporarily out of service. Disable the system undergoing maintenance to prevent unwanted alarms.

1. Via the FACP, command the individual TR-B200S-LF-WH/TR-B200S-LF-IV to activate using the associated sensor address. That sounder base should sound in approximately five seconds.
2. Via the FACP, command all TR-B200S-LF-WH/TR-B200S-LF-IV low frequency sounder bases to activate using group communication to all associated addresses. All devices on the loop should sound, and if a temporal tone is commanded, the tones can be synchronized to each other.

NOTE: Synchronization requires a power supply capable of producing the System Sensor synchronization pulses or a synchronization module.

When performing maintenance on connected smoke sensors, carefully note the location and address of each removed sensor. When re-installed, the TR-B200S-LF-WH/TR-B200S-LF-IV will confirm that address of the sensor matches the address stored in the sounder base memory. If there is a mismatch, this will be communicated to the FACP and the sounder base can be commanded to chirp at regular intervals until the correct head is installed.


If a replacement head is installed or address changes are required, the mismatch may be resolved at the panel by commanding the TR-B200S-LF-WH/TR-B200S-LF-IV low frequency sounder base to re-enter its address learning mode and adopting the address of the new sensor.

**FIGURE 4. WIRING DIAGRAM**

**(CONNECTED TO 24V POWER USING COMPATIBLE FACP WITH "SOUNDER BASE STANDBY POWER MONITORING" ENABLED)**

NOTE: Only use this wiring diagram when connecting to 24VDC power using a FACP listed in the table on page 1. Please consult your FACP manufacturer for panel-specific wiring configurations and special cases.


Additional Audible Visible devices may be connected to the same power supply or the the NAC output of the Fire Alarm Control Panel (FACP) to provide a synchronized communication of the alarm signal.



C0474TRG-24


**FIGURE 5. WIRING DIAGRAM (CONNECTED TO NAC OR 24V POWER; OPTIONAL EOL DEVICES FOR CONSTANT SUPERVISION)**

NOTE: Only use this wiring diagram when connecting to a NAC or a 24V power supply that does not support "sounder base standby power monitoring" (see page 1).



C0474TRG-25


**FIGURE 6. SYNCHRONIZATION DIAGRAM (FOR MDL SERIES SYNC MODULES ONLY)**



C1090-02


NOTE: Wiring shown for System Sensor MDL Series Sync Module. For additional wiring configurations, see your sync module manual.

**FIGURE 7A. ACTIVATING THE TAMPER-RESIST FEATURE**



C0144-00

**FIGURE 7B. REMOVING THE DETECTOR HEAD FROM THE BASE**



C1082-01